


Model 1015-00RSB

D-908-00

## Directions for Installation and Operation

**WIRING:** Connect in accordance with National and Local Electrical Codes. See suggested circuit below.



**Switch Rating:**  
10A 120Vac  
5A 208-240Vac  
125VA Pilot Duty 120-240Vac  
Timing Motor: 120V 60Hz  
Resistor For Operation  
On 240V 60Hz

### **CAUTION - RISK OF ELECTRIC SHOCK**

**ALL POWER TO THIS CONTROL MUST BE TURNED OFF AT THE MAIN PANEL BEFORE INSTALLING OR SERVICING. TURNING THE MANUAL CONTROL TO THE "OFF" POSITION DOES NOT PREVENT SHOCK HAZARD AT THE EQUIPMENT IT CONTROLS.**

**1A.** To omit any day or days of the week, locate day to be omitted on small dial. Raise set screws for the day to be omitted by turning **CLOCKWISE** until tight, but do not force.

**1B.** To cancel omission of any day or days, turn set **COUNTER-CLOCKWISE** for the day or days desired until set screw is flush with the small dial, and tight.

**2.** To set small 7 day dial to correct day of the week, grasp large 24 hour dial and turn in either direction until the correct day of the week appears below "Day Set" red dot and 12 noon on large 24 hour dial is below red pointer.

**3.** To set the correct time of day, grasp large 24 hour dial and turn in either direction until the correct time appears below red pointer.

**4.** To set program each 15 minute interval has a tab. First push all tabs down. Pull up tab or tabs as high as possible to close circuit Number One.  
**NOTE:** Circuit Number Two will automatically open when circuit Number One closes.

**5.** After a power failure, reset to correct time of day and day of week.

For service, return to nearest authorized Maple Chase Company Service Center.

**PARAGON**  
Electrical Products

Maple Chase Company  
2820 Thatcher Road  
Downers Grove, Illinois 60515  
Made in Mexico

Telephone +1 800 732 8400  
ISO 9002 registered

