


Model 44001-00

A-802-00

Directions for Installation and Operation

WIRING: Connect in accordance with National and Local Electrical codes. See suggested circuit below.




Contact Rating
40A 40A TUNGSTEN 120 Vac
1 hp 120 Vac
690 VA PILOT DUTY 120 Vac
TIMING MOTOR: 120V 60 Hz



CLOCK-OPERATED
SWITCH 521 H
E10597



LR70287



CAUTION - RISK OF ELECTRIC SHOCK

ALL POWER TO THIS CONTROL MUST BE TURNED OFF AT THE MAIN PANEL BEFORE INSTALLING OR SERVICING. THE CONTROL BEING IN THE OFF POSITION DOES NOT PREVENT SHOCK HAZARD AT THE EQUIPMENT IT CONTROLS.

TO SET TRIPPERS: Loosen thumb screw in tripper enough to slide tripper around dial. Set **ON** (Bright) tripper at time load circuit should close. Set **OFF** (Dark) tripper at time load circuit should open. Add trippers by loosening thumb screw enough to slip tripper on dial, making certain that screw tightens on dial ridge.

TO SET TIME OF DAY: Turn time dial (A) in **CLOCKWISE DIRECTION** until correct time is in line with the time pointer (B). **DO NOT TURN TIMER POINTER.**

MANUAL OPERATION: Dial (A) may be turned manually in clockwise direction to check switch operations. Switch may be hand tripped by moving hand trip lever to opposite position.

TO REMOVE MOVEMENT FROM CASE: Press spring clip, at right center of case, and lift movement out.

TO REPLACE MOVEMENT IN CASE: Insert tabs on the left side of time switch plate into holes in side of case. Push down and snap into place.



Maple Chase Company
2820 Thatcher Road
Downers Grove,
Illinois 60515
1-630-719-5600
Made in Mexico

Tech Support: 800-732-8400
Customer Service: 800-951-5526

Paragon Electric Canada, Ltd.
5785 Kennedy Road
Mississauga, Ontario L4Z 2G3
905-890-5956

120-1414B