

**STANLEY**<sup>®</sup>

# Digital Bar Timer™

## Slim Indoor Daily Digital Timer

Toll-Free Customer Support: 1.800.730.3707

### OPERATING INSTRUCTIONS:

What this timer does:

Your timer can be programmed to turn a lamp or other electric device on and off automatically, once per day.

Plug the timer into the wall and wait for at least 30 minutes to charge the built-in rechargeable battery. This will allow the timer to be programmed and keep time even when it is not plugged in. The timer must be plugged into the wall outlet to operate your lamp.

Before using the timer, make sure that the lamp works by plugging it into the wall outlet. While the lamp is on, unplug it from the wall.

Plug the lamp into the timer and plug the timer into the wall.

Your timer will turn your lamp on and off automatically.

### PROGRAMMING INSTRUCTIONS:

The first time you use the timer, press the reset button with a pointed object to reset and clear any previously set program. Be sure to charge the battery as noted above.

Slide the switch on top to **TIMER**.

① To set to the current time:

While holding the **TIME** button down, press **HOUR** until the current hour is displayed (noting AM or PM).

To set the current minute, hold the **TIME** button down and press **MINUTE** until the current minute is displayed.

The timer will display and keep the current time when the **TIME** button is released.

(Example: Display will read "TIME 4:30 PM")

② To set the time at which your lamp will turn ON:

While holding the **ON** button down, press **HOUR** until the desired "on" hour is displayed (noting AM or PM).

To set the "on" minute, hold **ON** and press **MINUTE** until the desired "on" minute is displayed. (Example: Display will read "ON 6:30 PM")

The timer will display current time when the **ON** button is released. To view the programmed "on" time, press **ON**.

③ To set the time at which your lamp will turn OFF:

While holding the **OFF** button down, press **HOUR** until the desired "off" hour is displayed (noting AM or PM).

To set to "off" minute, hold **OFF** and press **MINUTE** until the desired "off" minute is displayed.

(Example: Display will read "OFF 11:30 PM")

The timer will display current time when the **OFF** button is released. To view the programmed "off" time, press **OFF**.

### Always On Mode:

Slide the top switch to **ON** for "Always On" mode.

Slide the switch to **TIMER** to return to timer control.

**SAVE THIS INSTRUCTION!**