

# Digital Controls

## PE20000 Series Digital Pool or Spa Control Panels

For pool, spa or water feature applications, the I-Wave PE3 Series Wireless Control System includes one P1353ME mechanism that controls a total of three timed circuits, including single speed or two-speed filter pumps, cleaner/booster pumps, pool lights, spa lights and landscape lights. Countdown and override features allow programs to be interrupted for service and automatically resumed without reprogramming your system.

Intermatic makes it simple to convert your PE Series Digital Control into a Wireless Control System. Simply install a Panel Mounted Transceiver (RC650) and a Hand-Held Transceiver (PE950) to any PE Series Control, which allows the system to display the status of each of the three circuits as well as pool or spa water temperature, pool or spa thermostat set point, heating status and overall communication status.



PE20000



PE25300



PE25300F

### Applications

- Single Speed Pump/Booster Pump Combos
- Water Feature Applications
- Pool & Spa Lighting
- Two-Speed Pump/Booster Pump Combos
- Garden & Fountain Applications
- Landscape Lighting

### Specifications

**Case:** 16-1/2" (41.9 cm) high x 10-7/8" (27.6 cm) wide x 4-1/4" (10.8 cm) deep, 0.048" plastic enclosure beige finish.

**Knockouts:** One 1.09 diameter through hole, six combination 1/2"-3/4" knockouts, and three combination 3/4"-1" knockouts on the bottom. Two combination 1/2"-3/4" on the left side and one combination 3/4"-1" on the back. One knockout 1-3/4" x 2-3/4" on the right side for mounting switches or GFCI.

**Panel Rating:** 60 Amp 120/240 V.A.C or 120/208 VAC single phase

**Switch Rating:** P1353ME5

**Shipping Weight:** See table

**Agency Approval:** CSA/C-US

Model #	Description/Mechanism	Switch	Clock Supply Volts 50/60 Hz	Shipping Weight
PE20000	None	None	120 or 240	14.1bs (9.0 kg)
PE25300	P1353ME	3SPST	120 or 240	14.7 lbs (9.0 kg)
PE25300F	P1353ME w/Freeze Probe	3SPST	120 or 240	14.7 lbs (9.0 kg)