

28441_00441 Daily Digital Timer

TimeIt

Daily Digital Timer

2-Wire Polarized Outlet and Plug
120VAC 60Hz, 5A 600W Resistive Load
Customer Service: 1.800.730.3707

READ ALL INSTRUCTIONS - IMPORTANT!

Before using the timer plug it in for 10 - 15 minutes; then press the reset button


SET CURRENT TIME:

- 1 Press and hold the "TIME" button, then press the "HOUR" button to set the current hour.
- 2 Press and hold the "TIME" button, then press the "MINUTE" button to set the current minute.

SET PROGRAM:

- 1 Press and hold the "PROG" button 1 second to enter the program setting; you will see "PROG 1 ON" on the display.
- 2 Press the "HOUR" button to set the "PROG 1 ON" hour.
- 3 Press the "MINUTE" button to set the "PROG 1 ON" minute.
- 4 Press the "PROG" button 1 second and repeat step 2 and 3 to set "PROG 1 OFF".
- 5 After setting the "PROG 1 OFF" press the "TIME" button once to return to the current time

You can set up to 6 different ON and OFF times for your timer. To do so, just repeat step 2 to 4 for "PROG 2 ON", "PROG 2 OFF", "PROG 3 ON" etc...



MANUAL OVERRIDE:

Pressing the "MODE" button when the current time is being displayed will allow you to set the status of the timer:

- If "ON" is to the left side of the display the timer will be active until "MODE" is pressed.
- If "OFF" is to the left side of the display the timer will not activate until "MODE" is pressed.
- If no icon is to the left side of the display the timer will run on the program setting until "MODE" is pressed.

NOTES:

- 1 The unit you are plugging into the timer has to be on.
- 2 Make sure AM and PM are correct on the current time and in the program settings.

SAVE THESE INSTRUCTIONS!