

TimeIt

Weekly Digital Timer

2-Wire Polarized Outlet and Plug
 Rated: 120VAC 60Hz, 5A 600W Resistive Load
 Customer Service: 1.800.730.3707

SET CURRENT TIME:

- Press and hold the "TIME" button 3 seconds to set the current day; you will see the day flash.
- Press the "+" or "-" to set the current day.
- Press the "+" or "-" to set the current hour.
- Press the "TIME" button once more to set the current minute; you will see the minute flash.
- Press the "+" or "-" to set the current minute.


SET PROGRAM:

- Press and hold the "PROG" button 3 seconds to enter the program setting; You will see all the days of the week flashing on the top and "PROG 1 ON" to the left of the display.
- Press the "+" or "-" to set the "PROG 1 ON" days of the week that you want the timer to function.
- Press the "TIME" button once, then press the "+" or "-" to set the "PROG 1 ON" hour.
- Press the "TIME" button once more, then press the "+" or "-" to set the "PROG 1 ON" minute.
- Press the "PROG" button once and repeat step 2 to 5 to set "PROG 1 OFF".
- After setting the "PROG 1 OFF" press the "MODE" button once to return to the current time.

You can set up to 8 different ON and OFF times for your timer. To do so just repeat step 2 to 5 for "PROG 2 ON", "PROG 2 OFF", "PROG 3 ON" etc...

READ ALL INSTRUCTIONS - IMPORTANT!

Before using the timer plug it in for 10 - 15 minutes; then press the reset button



MANUAL OVERRIDE:

Pressing the "MODE" button when the current time is being displayed will allow you to set the status of the timer:

- If "ON" is to the left side of the display the timer will be active until "MODE" is pressed.
- If "OFF" is to the left side of the display the timer will not activate until "MODE" is pressed.
- If "AUTO" is to the left side of the display the timer will run on the program setting until "MODE" is pressed.

SET VACATION SECURITY:

Pressing the "TIME" and "PROG" buttons simultaneously will activate security mode. If "SEC" is to the right side of the display the timer will turn on randomly during different parts of the day. Simply press "TIME" and "PROG" simultaneously to disable "SEC".

NOTES:

- The unit you are plugging into the timer has to be on.
- Make sure AM and PM are correct on the current time and in the program settings.

SAVE THESE INSTRUCTIONS!