



GRÄSSLIN

TFC GROUP LLP

Talento Plus 371 - 372



- Daily and weekly program
- 50 Memory spaces
- Automatic summer time /winter time changeover
- 3 years running reserve
- Manual switch: FIX ON / FIX OFF
- Free weekday block formation
- Non-volatile memory (EEPROM)

Code: TALENTO371+ (single channel)

Code: TALENTO372+ (two channel)

Technical data
 Dimensions H x W x D (mm)
 Distributor cut-out (mm)
 Weight (g) approx.

Connection voltage

Power consumption at 230 V~ (AC)

AC switching capacity
 - ohmic load (VDE, IEC)
 - inductive load cos. ϕ 0.6
 - Incandescent lamp load

DC switching capacity
 24 VDC/50 VDC/220 VDC

Switching output

Switch contacts

Ambient temperature

Protection class

Accuracy

Power reserve

Shortest switching time

Programmable every

Memory spaces

Manual switch

Block formation of weekdays

Holiday program/date range

Random generator

Switching state display

Pulse switching commands

Cycle switching commands

Summer/winter time changeover

External output

- Override

- Countdown

DCF 77 input


Max. Terminal capacity

Connection type


Sealable

talento 371 plus	talento 372 plus
45 x 35 x 60	45 x 35 x 60
46 x 36	46 x 36
170	170
230 V/50-60 Hz 110-120 V/50-60 Hz 24 V AC/DC	230 V/50-60 Hz 110-120 V/50-60 Hz 24 V AC/DC 12 V AC/DC
5 VA	5 VA
16 A/250 V AC 8 A/250 V AC 1000 W	16 A/250 V AC 8 A/250 V AC 1000 W
800 mA/300 mA/150 mA	800 mA/300 mA/150 mA
potential-free	potential-free
1 changeover contact	2 changeover contact
-25°C (*) ... +55°C	-25°C (*) ... +55°C
II	II
typ \pm 2,5 s/day at +20°C	typ \pm 2,5 s/day at +20°C
3 years from factory at +20°C	3 years from factory at +20°C
1 min	1 min
min	min
50	50
automatic/preselection Fix ON/Fix OFF	automatic/preselection Fix ON/Fix OFF
free assignment	free assignment
-	-
-	-
yes	yes
-	-
-	-
automatic / freely selectable / off	automatic / freely selectable / off
-	-
-	-
4 mm2 captive \pm screw terminals	4 mm2 captive \pm screw terminals
yes	yes

talento 371, 372, 471, 472 plus



talento 371 plus



talento 372 plus

