

## Tork 601A

<http://waterheatertimer.org/GE-timers-and-manuals.html>

### Single-Outlet 24 Hour Mechanical Outdoor Timer

This timer is for outdoor use only.  
Ideal for controlling landscape lighting and Christmas lights.

It also controls small pumps, fountains, motors, etc.

Timer features 18" cord.  
Plug timer into outdoor GFCI protected outlet.

Timer has one 125 Volt grounded outlet located on bottom of timer. 1250 Watts. Typical 50-mini-bulb Christmas string is 25 Watts

#### RATINGS

- 125VAC 15A Resistive & General Purpose
- 125VAC, 1250W Tungsten
- 125VAC, 1/2HP

Length 6 In. Width 3 1/8 In. Depth 1 5/8 In.

96 captive pins located around timer dial allow times to be set each 15 minutes.

Move pins in-or-out with fingernail or pen to set timer on-off functions.

Minimum time setting is 15 minutes.

Maximum time setting 23 3/4 hours.

Set multiple ON/OFFs each day.

Timer repeats every 24-hours.

Dial is divided into daylight and nighttime hours.

Nighttime PM Hours are on dark background.

AM Hours are on light background.

To set current time, rotate dial clockwise until current time lines up with arrowhead located on inner dial.

Reset time after power outage.

Manual ON/TIMER switch is located on inner dial.

Set override to timer for program to operate.

To override timer and turn on Load, move override to ON position.

## Product Images



Manual ON-Timer switch



Pins out = Timer ON