



Westinghouse

3-Outlet Ground Stake

All Weather 6-Outlet Safety Power Station with Digital Photocell Timer and 10ft (3.05m) 14/3 Power Cord

Rated: 125V/15A/1875W, 60Hz

Toll-Free Customer Support: 1.800.730.3707

OPERATING INSTRUCTIONS:

Insert the ground stake 6 inches (15.24cm) into the ground.

Press the button to cycle through the different operating modes:

On LED	Mode Description
F	Always Off
O	Always On
1 - 9	On at Dusk, Off after 1-9 hours
1. - 9.	On immediately, Off after 1-9 hours (note the period after the number)
d	On at Dusk, Off at Dawn

POWER INDICATOR:

When power is On to the Ground Stake, the LED marked "ON" will light up.

CAUTION:

- ① Risk of Fire, Not for permanent installation. Use only with a total of 12 Ampere maximum Christmas tree or other seasonal lighting products. Do not install or use this product for more than a 90-day period.
- ② If using Christmas tree or decorative lighting products that are not marked with an ampere rating, connect no more than 140 screw-base lamps (C7 or C9) or 12 strings with midget (push in) lamps to this cord set.
- ③ Cord sets shall be plugged into a GFCI-protected receptacle.
- ④ If using an outdoor-use cord set for an extended period of time (greater than 90 days), please consider hard wiring a permanent outdoor-use receptacle rated for year-round use in the area that power is needed. Please contact a licensed electrician for proper installation of permanent wiring.
- ⑤ After completion of installation, the connector shall be maintained a minimum of 6 inches (15.24cm) above ground.

SAVE THESE INSTRUCTIONS!