

Tork 651A & 652A

PHOTOCELL CONTROLLED MECHANICAL OUTDOOR TIMER WITH ONE OR TWO OUTLETS

Timer turns ON automatically at dusk

Rotate dial to choose options

Grounded outlet on bottom of timer

Plug timer into 125 Volt GFCI protected outlet.
Do not plug timer into extension cord.
Indicator light shows when timer has power.
Timer turns ON automatically at dusk.
Plug lights, small pump, fountain, motor into grounded outlet located bottom of timer.
Rotate dial to choose timer function.

651A: 6.5" cord and **one grounded outlet**

652A: 6.5" cord and **two grounded outlets**

APPLICATIONS

- Ideal to control landscape lighting and Christmas lights
- Control small pumps, fountains, motors, etc

TORK 651-2A Timer Mechanical Voltage 125 Watts
1000W Amps 1.5 HP @ 120V

RATINGS 651A

125VAC 15A Resistive & General Purpose
125VAC, 1000W Tungsten
125 VAC, 1/3 HP, TV-4

RATINGS 652A

(total for two outlets)
125VAC 15A Resistive & General Purpose
125VAC, 625W Tungsten
125 VAC, 1/3 HP, TV-5

Receptacle Type Grounded

Color Gray Length 5 3/4 In.

Style Plug In

Receptacle on Bottom of Timer

Standards cULus

Features Photocell Controlled

652A Same as GE 15112 Two-outlet timer

FEATURES

- Choice of settings:
 - ON at dusk & OFF 2, 4, 6, 8 hours later
 - ON at dusk, OFF at dawn
 - ON continuously
 - OFF

Tork 651A Images

